

Ballast Compatible SmartFit Series

T8 Series Linear LED Tube



Product Description

The SmartFit Ballast compatible T8 LED tube can work with most popular ballasts (Instant Start, Rapid Start, Dimmable Ballast) capable of replacing your existing fluorescent T8 lamps without any additional wiring. It provides exceptional LED lighting with reduced energy and maintenance costs.

Tube Features

- * Direct Replacement - works with existing fluorescent T8 lamp fixture with Instant Start/Rapid Start and Dimmable/Emergency ballasts
- * Beam design - 270° light emitting area
- * Exceptional efficacy -100 LPW
- * DLC 3.0 standard listed (4Ft. & 2Ft.)
- * No flickering
- * 5 years Warranty



Product Model								
Product	Lamp Power (W)	System Power (W)	Luminous (lm)	CCT (K)	CRI	Lifetime (hrs)	Dimension (mm)	Beam Angle(°)
L24T8-XY-08P-G2-EB	8	10	1050	4000/5000	80	50000	Φ 26x600	160
L36T8-XY-10P-G2-EB*	10	12	1150	4000/5000	80	50000	Φ 26x900	160
L48T8-XY-12P-G2-EB	12	15	1650	4000/5000	80	50000	Φ26x1200	160
L48T8-XY-15P-G2-EB	15	16	1850	4000/5000	80	50000	Φ26x1200	160
L48T8-XY-18P-G2-EB	18	21	2350	4000/5000	80	50000	Φ26x1200	160

* At present, there is no inventory in USA

TOPSTARTM